



# V2

## USER GUIDE



# OMICRON v2 USER GUIDE

## ASSEMBLY


The Omicron v2 vaporizer is the next evolution of the world's first non-flame powered portable extract vaporizer. The only one to use pure extract oils with no need for carrier agents or cotton in the cartridge. The only one that allows you to load the cartridges with your own extract oils.

Omicron v2, the evolution of vaporization has arrived.


- Prerequisites:
- Omicron v2 body, battery, base cap and head.
  - Omicron cartridge already filled with no more than 1 gram of extract.

**1.** Remove the white cap from the top of the cartridge. The top is the end opposite of the threads.


**2.** Insert base cap into Omicron v2 body and tighten.




**3.** Insert battery into top of the Omicron v2 body, orientated negative end towards the Base cap.



**4.** Place head on to top of Omicron v2 body and tighten.



Remove the white cap from the top of the cartridge before use.



### OMICRON v2 SAFETY LOCKOUT

To toggle the lockout feature of the power button on your Omicron v2, quickly press the power button 5 times in a row until the blue light flashes 3 times. To test the current on/off state, just press the power button once. If the blue light comes on the lockout is deactivated. The safety lockout feature is great to prevent your Omicron v2 from accidentally being activated.



# OMICRON v2 USER GUIDE

## PRIMING AND USE


Prerequisites:

- Omicron v2
- Cartridge already filled with no less than .5 grams and no more than 1 gram of extract and attached to your Omicron v2.

- 1.** Depending on how long your cartridge has been stored for, the temperature, orientation of it during storage and thickness of your extract, the cartridge may or may not need priming. All newly filled cartridges should be primed before use. To test, place the mouthpiece in your mouth and try to gently suck air through using only your mouth sherlock style, not your lungs, while pressing the button for 2-4 seconds.

If you feel and taste vapor, go to step 3.

If you did not feel or taste vapor, go to step 2.




- 2. Priming:** **Set up your Omicron v2 for 3.7 volts for the priming of ALL cartridges.**

Press and hold the power button on the Omicron v2 for 3 seconds (1.5-2.5 ohm cartridges) and 6 seconds (2.5-5.0 ohm cartridges) and let go.

Immediately try to gently suck air through using only your mouth sherlock style, not your lungs. Keep repeating this cycle until you can feel and taste vapor, sometimes you will hear or feel a tiny pop and then air will start flowing.


Never inhale hard using the Omicron v2, this will result in extract being pulled into the air tube causing clogging.



- 3. A.** *Using your lungs*, very slowly inhale while holding down the power button for no longer than 10 seconds (3 seconds at 7.4volts). Some users find it difficult to inhale slowly enough and have greater success using method B.

**B.** *Using your mouth*, very slowly suck, filling only your mouth with vapor while holding down the power button for a maximum of 6-12 seconds (3 seconds at 7.4volts). Remove the Omicron v2 from your lips and inhale the vapor in your mouth deeply. For both methods, continue drawing air through the cartridge for 2 - 3 seconds after releasing the power button to help prevent clogging.

**Always allow the cartridge to cool between hits.**





# OMICRON v2 USER GUIDE

## FLOW CHART


Remove the white cap from the top of the cartridge. Place the mouthpiece in your mouth and try to gently suck air through using only your mouth sherlock style, not your lungs while holding down the power button for 2-6 seconds.

If you feel and taste vapor



**!!WARNING!! Cartridge is HOT during use, avoid touching it.**

If you did not feel or taste vapor



**A. Using your lungs**, very slowly inhale while holding down the power button for no longer than 10 seconds (3 seconds at 7.4volts). Some users find it difficult to inhale slowly enough and have greater success using method B.

**B. Using your mouth**, very slowly suck, filling only your mouth with vapor while holding down the power button for a maximum of 6-12 seconds (3 seconds at 7.4volts). Remove the Omicron v2 from your lips and inhale the vapor in your mouth deeply. For both methods, continue drawing air through the cartridge for 2 - 3 seconds after releasing the power button to help prevent clogging.

**Always allow the cartridge to cool between hits.**

**Set up your Omicron v2 for 3.7 volts for the priming of ALL cartridges.** Press and hold the power button on the Omicron v2 for 3 seconds (1.5-2.5 ohm cartridges) and 6 seconds (2.5-5.0 ohm cartridges) and let go. Immediately try to gently suck air through using only your mouth sherlock style, not your lungs.



**Never inhale hard using the Omicron v2, this will result in extract being pulled into the air tube causing clogging.**



**!!WARNING!! Cartridge is HOT during use, avoid touching it.**

Vapor flow now?

Yes

No

Try again  
10 times

Vapor flow now?

Yes

No

Take a pin or straightened paper clip and VERY GENTLY insert it into the air tube until it touches the heating element at the bottom.

Vapor flow now?

Yes

No

Please open a support ticket at [www.w9tech.com](http://www.w9tech.com) and you will be contacted to have your problem resolved.

Increase the size of your hit by slowly inhaling for no more than 6 seconds (3 seconds at 7.4volts). Hold in your hit for 5 seconds while the cartridge cools and repeat until your lungs are full.

**Sherlock Style:** Increase the size of your hit by slowly using your mouth only to inhale the vapors into your mouth for no more than 6 seconds (3 seconds at 7.4volts). Release the power button and quickly inhale the vapors that are in your mouth into your lungs and repeat the cycle until your lungs are full. Let the cartridge cool for 5 seconds between hits.


When your session is finished, place the white cap back onto the cartridge, sit back and relax!





## OMICRON v2 USER GUIDE

### MAINTENANCE INSTRUCTIONS



Your Omicron v2 Vaporizer has been designed to be easy to care for and maintain.

By following these simple maintenance steps, you will keep your Omicron v2 Vaporizer performing at peak performance.

Depending on your frequency of usage, the electrical contact points should be cleaned at least once every 3 - 7 days. The Omicron v2 vaporizer uses relatively low voltage to operate and even a small amount of residue on the contact points and/or threads can reduce the voltage flow, impeding the performance of your Omicron v2. **Any residue bridging the gap between the threads and center post on your Omicron v2, could cause a very dangerous electrical short resulting in physical injury to yourself and damage to the battery and/or your Omicron v2. Keep It Clean !**

- A. To clean the electrical contact points and threads, take a cotton swab (Q-Tip) and dip one end into some Isopropyl Alcohol (ISO). The higher percentage of purity, the better, try to use as close to 99% ISO as you can.
- B. Using the ISO dampened end of the cotton swab, gently scrub and clean any residue from all the contact surfaces and threads on all your **cartridges and Omicron v2**. The contact surfaces are all the areas that make contact with each other when a cartridge is screwed into the Omicron v2.
- C. Once cleaned, use the dry end of the cotton swab to help the drying process by gently running it over the areas just cleaned. Be careful that no cotton gets left behind on any surfaces or threads.

After every thing is completely dry, lightly touch the contact areas and threads with your fingers. If you feel any tacky areas, please repeat the cleaning procedure steps A - C again until all the contact areas and threads are tack free.

**DO:** Use ISO to clean the contact areas and threads on all your cartridges

**DO:** Use ISO to clean the contact areas and threads on your Omicron v2

**DO:** Keep your Lithium Ion 14650 batteries charged and in good physical condition

**DON'T:** Submerge your cartridge, Omicron v2, battery or charger in any liquid

**DON'T:** Try to clean out a cartridge by filling it with ISO

**DON'T:** Leave behind any lint or cotton on the cleaned surfaces or threads

**DON'T:** Screw a cartridge on to the Omicron v2 with out cleaning both first

**DON'T:** Allow a fully charged battery to sit in the charger for extended periods of time

**AVOID:** Using cartridges that have had their seals damaged and/or thin oil put in them, causing them to leak.




## OMICRON V2 USER GUIDE


### CARTRIDGE FILLING INSTRUCTIONS

- Prerequisites:
- Select a level, flat and smooth heat resistant surface to work on  
i.e. granite kitchen / bathroom counter
  - Jet flame lighter recommended, regular lighter will also work
  - Cartridge Fill Tool

- 1.** Hold the cartridge upright, grasping it between your thumb and forefinger just above the threads.



- 2.** Place Fill Tool onto the top of the cartridge. The air tube hole will be covered by the deflector built into the Fill Tool.



The Fill Tool has been designed for a very tight precise fit onto the top of the cartridge. Some force might be required the first time a new cartridge gets fitted with the Fill Tool.




## OMICRON V2 USER GUIDE


### CARTRIDGE FILLING INSTRUCTIONS

- 3.** If your extract is in a vial, place the vial into the Fill Tool upside down and with the vial cap off (3a). If your extract is not in a vial, just load it directly into the Fill Tool (3b). Remember ! **0.5 gram minimum and 1.0 gram maximum.**

**3a.**



**3b.**





## OMICRON V2 USER GUIDE


### CARTRIDGE FILLING INSTRUCTIONS

The goal during cartridge filling is to get all your extract into the bottom of the cartridge using as little heat as possible, but as much as needed. We want to avoid any cold spots on the cartridge walls to help prevent any melted extract from solidifying on the way down and causing an air gap or blockage of any kind.


- 4.** Gently start to apply heat with your torch lighter on a low setting. Preheat the center of the cartridge first, just above your fingers <sup>①</sup> until you feel the cartridge body get warm. Keep rotating the cartridge so it heats all around evenly. Once you feel heat working down, move the flame slowly up the cartridge toward the top <sup>②</sup> with plenty of heat (just short of smoke being visible). As long as your fingers don't get too hot in which case stop, let it cool, and repeat again if necessary. If the cartridge gets too hot to hold, you are applying too much heat.

**DO NOT overheat the cartridge!**

**4a.**



**4b.**








## OMICRON V2 USER GUIDE

### CARTRIDGE FILLING INSTRUCTIONS


- 5.** Keep applying heat with your torch lighter on a low setting, moving the flame up and down from the top of the vial 5a or Fill Tool 5b down to just above your fingers. Keep rotating the cartridge so it heats all around evenly. You should see your extract start to liquefy and run down the Fill Tool and into the cartridge.

**DO NOT overheat the cartridge!**

**5a.**



**5b.**






## OMICRON V2 USER GUIDE

### CARTRIDGE FILLING INSTRUCTIONS


- 6.** Once the extract begins to flow into the cartridge, move your torch lighter back down to heat the Fill Tool and cartridge until all of your extract is in the cartridge. After about 25 - 30 seconds of heating, the part of the cartridge under your fingers will get really hot, stop heating. Let the Fill Tool, vial and cartridge cool down for 3 minutes before touching them!!!

**DO NOT overheat the cartridge!**

**6a.**



**6b.**






## OMICRON V2 USER GUIDE

### CARTRIDGE FILLING INSTRUCTIONS


- 7.** Once cool, remove the vial (7a) and then the Fill Tool (7b). The cartridge is now ready for use.

**7a.**

!!! Let the Fill Tool, vial and cartridge cool down before touching them !!!




**7b.**



- 8.** If you are going to store the cartridge then place the white cap on the end.


Place white cap on for storage, or leave off for instant use.





# OMICRON V2 USER GUIDE

## FAQ's



**Q.** What are the DO's and DON'T's?

- A.** **DO:** Take the white cap off the cartridge before use and replace after use  
**DO:** Pull air through the cartridge VERY SLOWLY  
**DON'T:** Blow air into the cartridge, you will damage the seals  
**DON'T:** Get any oils, waxes etc. into the air hole during filling  
**DON'T:** Excessively heat below the top 3/4 of the cartridge or you will damage the seals  
**DON'T:** Inhale hard, you will suck too much extract into the vaporization chamber causing a clog  
**AVOID:** Extract oils that are too thin or runny at room temperature, or poorly processed / purged

**Q.** Will the Extract cartridges fit other ecig batteries?

- A.** The refillable Pure Extract cartridges were specifically designed for the Omicron, Omicron v2, Persei and O-PHOS only.

**Q.** What types of essential oils can I use?

- A.** Any essential oil that will liquify with heat and thicken at room temperature that was not produced using water or ice extraction. There can be no plant material left in the extract i.e. bho, earwax, putty, shatter, cO2, nitro etc.

**Q.** Can I remove the white cap?

- A.** We recommend removing the white cap before use and putting it back on after your session if you will be storing the cartridge in a warm area on its side. Otherwise the white cap is not needed.

**Q.** My cartridge is leaking, what can I do?

- A.** The most common reasons for leaking cartridges are:
- Overheating the cartridge during filling and the seals are now damaged
  - Blowing air into the cartridge trying to clear a clog, the seals are now damaged
  - Inhaling too hard, try sucking very slowly and lightly
  - Inhaling too soft, try sucking a little harder, but not too hard
  - Over filling the cartridge, 1 gram is the maximum capacity
  - Using oil that is too thin or low quality / poorly processed / purged will leak

If your seals are damaged, it is best to reclaim your extract by turning the cartridge upside down, heating it and collecting the extract that drips out to put into a new cartridge.

**Q.** I hear bubbling sounds when I inhale, is this normal?

- A.** No, bubbling is caused by extract that is too thin at room temperature and/or has impurities in it from not being processed / purged correctly. These extracts are not recommended and will cause your cartridge to clog, leak and generally underperform.

**Q.** My cartridge is defective, what can I do?

- A.** We recommend to test every cartridge before use by connecting it to the Omicron v2 **before** filling it with extracts. Our battery/cartridge tester, available separately, is the recommended way to test your Omicron v2 and cartridges. You can hold down the power button while looking down the air hole. You should see one of the elements glowing brightly and feel the cartridge getting warm. There are no refunds or exchanges on cartridges for hygienic reasons. Packs of cartridges are sold as buy 4 get one free to insure against any defectives.



## OMICRON V2 USER GUIDE

### FAQ's



**Q.** How long does a cartridge last?

**A.** We claim that they will last a minimum of 400 hits or 1 gram of extract. Some users experience a lot more, but 400 is the minimum.

**Q.** How long does the battery last?

**A.** The battery is guaranteed for 14 days and a fully charged battery will last for about 200 6 second hits. Our duration is a conservative figure, based on half of the calculated number. The calculation you can use to estimate your number of hits based on your hit length is:  
*A 3.7 V battery and a 2.4 ohm cart will draw about 1.542 amps of current. ( $I=V/R$ )*  
*So a 1000 mAh battery will last about 0.65 hr (1.0 amp-hr/1.542 amps) or about 39 minutes of use.*  
6 second hits = 390 hits  
5 second hits = 468 hits  
4 second hits = 585 hits

**Q.** How long does the battery take to charge?

**A.** The answer to this depends on the remaining charge still left in your battery and which battery type you are charging. For an empty battery to fully charge requires approx. 3.5 hours. When in charging mode, the light on the charger will be solid **Red** and once charging has completed the light will turn either solid or flashing **Green** depending on the state of the charge.

**Q.** My blue light flashes as soon as I press the button, what is causing this?

**A.** If the blue light flashes as soon as you press the button, that is the low battery warning signal. Your battery is depleted, remove it from the Omicron v2 and fully charge it before using it again.

**Q.** How long is the warranty on the Omicron v2?

**A.** The Omicron v2 has a Limited Lifetime Warranty against manufacturer defects. The charger is guaranteed for 30 days and batteries for 14 days. Your invoice from an authorized dealer is needed for any warranty claims.

**Any Omicron v2's bought from an auction site such as eBay, have no warranty.**

**Q.** Can I charge LiFePO4 batteries in the charger included with the Omicron v2?

**A. NO, DO NOT** charge any other battery types except for those included in your Omicron v2 kit or serious personal injury could occur.