



# VIVANT | RIFT

Beyond Limits

# **USER MANUAL**

Read carefully before using the device and save these instructions.

#### Disclaimer

This appliance can be used by person aged from 18 years and above and persons with reduced physical, sensory or mental capabilities or lack of experience and knowledge if they have been given supervision or instruction concerning use of the appliance in a safe way and understand the hazards involved.

- \*Children shall not play with the appliance.
- \*Cleaning and user maintenance shall not be made by children without supervision.

# **USER MANUAL**

Table of Contents	Page
1. An Introduction to Your New RIFT Device	2
2. List of Components	4
3. Getting Started	6
4. Operating Instructions	10
5. Cleaning your RIFT	19
6. Safety Information	26
7. Warranty	31
8. Company Contact Information	32

#### Introduction

Vivant RIFT™ is the most innovative loose leaf and concentrates vaporizer made by our company – a true treasure among the plethora of vaporizers in the market. It is designed for the most discreet user seeking the highest quality vaping experience instantly on-the-go. Designed for both dry-herb and concentrates, Vivant RIFT ™ is spearheading the industry to new level. Vivant RIFT ™ uses a revolutionary technology – RIFT technology which guarantees zero off-gassing or oxidation – unlike the plethora of lower quality, common ceramic heaters used in the industry. In addition to introducing this revolutionary heating technology, we bring to you a new concept of a removable heater unit, giving you access to clean the entire device so you can collect reclaim and taste the nuances in every fresh bowl of material.

#### Some features of the kit:

- · RIFT heating element technology
- · Removable heater unit
- . Three sections can do flower and concentrates at the same time
- · No need to use a grinder to vaporize your flower
- · 0.69-inch LED screen
- Resealable mouthpiece reduces odor and prevents dust build-up the air pathway
- Firmware upgradable

#### Introduction



Loading Chamber

# List of Components

#### The RIFT kit comes with the following:



1 \* Extra Cleaning/Packing Rod With Silicone Key Chain Cover

3 \* Stainless Steel Concentrate Pad 1 \* Quick Guide



# List of Components







Mouthpiece Inner Silicone

# **Getting Started**

1. Quickly press the power button 5x to turn the device on or off.



#### 1. To load flower material



• Reverse or remove the mouthpiece.



 hold the device upside down, locate the lock switch on the bottom of the door and open the loading chamber by sliding the switch backwards.

# Getting Started



#### **Getting Started**

#### 2. To load concentrates and oils



Insert the food grade, stainless steel meshes into the three partitions of the bowl. Press the power button for 5 seconds to engage Turbo Mode heating this will help you to melt the concentrates into the mesh more easily. After a brief heating time, go ahead and load concentrates/oils into the meshes.



Put different flavors in different sections – mix and match your flavors according to your liking!



#### 1.Menu:

 Press and hold the "M" button to go into menu. Options are as follows: FLOWER, CONCEN-TRATE, CUSTOM, Vibrate, and Temp Unit.



 Scroll through the options with the +/- buttons.



 Single press the "M" button to enter the option you want.



 Enter "Vibrate" to select between vibration on or off.



 Enter "Temp Unit" to select Celsius or Fahrenheit as the temperature unit.

#### 2. Settings:



a.FLOWER - Scroll through the menu to "FLOWER" and single press the "M" button to enter selection.



b. CONCENTRATE - Scroll through the menu to "CONCENTRATE" and single press the "M" button to enter selection.



c. CUSTOM - Scroll through the menu to "CUSTOM" and single press the "M" button to enter selection.




#### 3. Modes:

Both Session and Turbo Mode can be used in any setting (FLOWER, CONCENTRATE, CUSTOM)

#### a. Session Mode

 Quickly press the power button 3X to activate the session.



FLOWER: 421°F(216°C), 408°F(209°C),

396°F(202°C),383°F(195°C),

370°F(188°C)

CONCENTRA: 455°F(235°C), 442°F(228°C),

432°F(222°C),421°F(216°C),

410°F(210°C)

CUSTOM: 248°F(120°C) - 455°F(235°C)





 Quickly press the power button or "M" button to set temperature.

#### CUSTOM:

Double click "M" button to adjust timer, single click "M" to select. (Time range:  $20s\sim300s$ )

Session timer is 2 min for FLOWER & CONCENTRATE settings, it is adjustable up to 5 min for CUSTOM setting.



before the session is over by double pressing the "M" button. The device will vibrate once it reaches the select temperature.



 Turn off session with 3 presses of the power button.



#### a. Turbo Mode

 Long press and hold the power button to activate the Turbo mode. (The Turbo mode can be activated any time, even durning a session.)



 When the bowl temperature is signficantly low, the device will notify you by vibrations before heating and once heating is over.



 To use Turbo Mode for on demand vaping, once the initial heating is complete (the device will vibrate to notify you), simply press the power button while you are taking a hit.



 Turbo Mode will automatically raise temperature to the maximum for Flower and Concentrate setting for on-demand performance. It will be adjustable under Custom setting.

Tip: Once initial heating is complete, you no longer need to wait for any vibration notification. Simply press and hold the power button to vape. If re-heating is necessary, the device will notify you by vibration when you hold the power button.



### Quick Cleaning:

1.Open the loading chamber.



Wipe down the heating module and all related parts with a cue tip.



### Thorough Cleaning:

1. Open the loading chamber.



2.Remove the packing tool.



Flip the chamber lock in the direction of the arrow to unlock the loading cap.



4.Remove the loading cap.



5.Remove the heater module.



6.Dip the cue tips in a 50% alcohol solution. Wipe down the heating module and all related parts with a cue tip.





7. Use the custom cleaning brush to clean the air tube.

8. Soak the heater module and related parts (seals, mouthpiece, screens) with a non-abrasive cleaning solution, dry them off with cue-tips and paper towels, and air dry for a few hours.

Tip: Quickly blowing water / liquid out of the heating module and performing a dry burn with the loading cap open will speed up drying tremendously.



Once the parts are dry, insert the heater module.



10. Insert the loading chamber at a 30 degree angle into the pivot point on the body as show in the photo.



11. With the chamber lock in the unlock position as shown by the circle, press the other side of the cap down until it is flat.



12. Flip the chamber lock back to lock it.

Your RIFT is built with three temperature sensors – one for the heater, one for the circuit board, and another for the battery. The built-in safety features prevents battery discharge when the circuit board is too hot, automatically pauses battery charging when the battery is too hot, and prevents battery discharge when the battery is too hot. However, users should only use the device for its intended purposes with additional safety precautions. These include the following:



1.KEEP THE DEVICE AWAY FROM WATER, RAIN, OR ANY LIQUID THAT CAN SHORT THE BATTERY AND DESTROY THE CIRCUIT BOARD. This includes placing the device in moist environments such as steam room at a spa.

**KEEP DRY** 



2.DO NOT TOUCH THE BOWL OF THE HEATER following use – it may be very hot and can cause serious burns. It takes approximately 5 minutes to cool down to room temperature.

#### **CAUTION HOT**



 DO NOT ATTEMPT TO REMOVE THE HEATER WHILE IT IS HOT. Allow the heater to cool completely (approximately 5 minutes in room temperature) before removing it for cleaning.



4.The display will say "Charge Protect" to indicate that it is not currently charging the battery. It will automatically disappear when the battery cools enough for taking a charge.

Charge Protect



5.The display will say "Device too hot" if the circuit board is too hot. This may occur after extreme consecutive heat cycles in hot weather and when no air is flowing through it. It will automatically go away once the board cools.

Device too hot



6.The display will say "No heater" if it is not detecting the heater. Sometimes after a long period of time, residue can build up and may potentially prevent electrical contact between the heater and the body of the device. If you see this, remove the heater and thoroughly clean the electrical contacts on the device and on the heater.

No heater





8.DO NOT BANG OR SLAM DEVICE AGAINST A HARD SURFACE to remove material, as that may damage the body, hooks, or scratch the exterior. VIVANT will not warrantee damage to the device due to user negligence. Simply use the packing tool to remove material and tap on the device with a finger to completely empty the bowl.



9. Running multiple, consecutive sessions at the highest temperature setting (~455F or 235C found in Custom or Concentrate Settings) may cause the loading cap on the device to get too hot to touch for some people. Please be aware of this and look for additional protective accessory from us in the near future. You may find accessories on our website when they become available.



 KEEP THE DEVICE AWAY FROM THE REACH OF CHILDREN.

#### Warranty

#### Vivant Product Replacement

This warranty provides free replacement of an authentic Vivant product if it malfunctions due to manufacturing defects. This warranty does not cover any damages outside of expected normal use.

#### Void of Warranty

Any one of the following conditions will void the warranty:

- 1. Failure to provide original receipt of purchase.
- Product failure or damage due to improper use or unauthorized repair or alteration.
- Product failure or damage due to the use of excessive force or user negligence (i.e. dropping the device, submerging the device in liquids, etc.).
- Product failure or damage caused by using incompatible parts or wires (i.e. using the wrong power cable, etc.).

Voiding the warranty is not limited to the conditions stated above. This warranty only covers authentic Vivant brand products and is valid for two years from the user's date of purchase.

#### **Contact Information**

### Vivant Inc

#### Address:

3589 Harbor Blvd, Costa Mesa, CA 92626

Email: info@vivant.com

Tel: 1-844-8-vivant (1-844-8-848268)

Web: www.vivant.com